

COSSOR 220 V.S.

2-VOLT VARIABLE MU. S.G.

This valve is a screened grid tetrode of the variable-mu type and has a relatively short grid base. For this reason it requires only a 9-volt grid bias battery to give adequate control of stage gain. By virtue of its characteristics this valve has a low high-tension consumption, and is capable of very high stage gain when associated with suitable coils. Like other Cossor screened grid valves, it has a very low grid-anode capacity of the order of .001 micro-microfarads.

TECHNICAL DATA

For Super H.F. Amplification.

Filament Voltage	2
Filament Current (Amps.)2
Impedance (Ohms) .. 400,000	} at { V_a . 150 V_{sg} . 60 V_g . 0
Mutual Conductance 1.6 m.a./v.	
Maximum Anode Voltage	150
Grid Bias Variable	0 to -9 v.
Anode Current for 150 Anode Volts with -1.5 volts Grid Bias (Average)	1.6 m.a.
Normal Working Anode Voltage	120
Positive Voltage on Screen Grid	60-80

