

COSSOR D.V.S./PEN.

16 VOLT ·25 AMP. INDIRECTLY HEATED VARIABLE MU H.F. PENTODE

The Cossor D.V.S./Pen. is a variable-mu high frequency screened pentode, and generally speaking it may be used in place of any reasonably equivalent screened grid valve, when it will give results equal to or better than previously experienced, according to the coupling used. The suppressor grid is brought out to a separate pin in the seven-pin base type, which makes possible the use of the valve in various special ways, such as for frequency changing; negative potential applied to this grid will greatly decrease the impedance—a function that may be used in special sets for simultaneously decreasing the gain and flattening the tuning, permitting the most perfect quality from the local station. The valve is also available with five-pin base, where the suppressor grid is connected to cathode.

TECHNICAL DATA

Heater Voltage	16
Heater Current (Amps.)	·25
Maximum Anode Voltage	200
Maximum Auxiliary Grid Voltage	100
Mutual Conductance at V_a 200, V_{ag} 100, V_g 0	3·0 m.a./v.
At V_a 200, V_{ag} 100, V_g — 1·5	2·0 m.a./v.
Negative Grid Voltage (Variable)	— 1·5 to — 20

